

USB4™ USB3 Tunneling Compliance Test Specification

Date October 2021

Revision: 1.2

Copyright © 2021, USB Implementers Forum, Inc.

All rights reserved

THIS SPECIFICATION IS PROVIDED TO YOU “AS IS” WITH NO WARRANTIES WHATSOEVER, INCLUDING ANY WARRANTY OF MERCHANTABILITY, NON-INFRINGEMENT, OR FITNESS FOR ANY PARTICULAR PURPOSE. THE AUTHORS OF THIS SPECIFICATION DISCLAIM ALL LIABILITY, INCLUDING LIABILITY FOR INFRINGEMENT OF ANY PROPRIETARY RIGHTS, RELATING TO USE OR IMPLEMENTATION OF INFORMATION IN THIS SPECIFICATION. THE PROVISION OF THIS SPECIFICATION TO YOU DOES NOT PROVIDE YOU WITH ANY LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS.

All product names are trademarks, registered trademarks, or service marks of their respective owners.

Revision History:

Revision	Issue Date	Comments
1.0	June 2020	First Release
1.1	January 2020	With editorial corrections and test fixes
1.2	October 2021	With corrections and clarifications. References the USB4 Specification, Version 1.0 with Errata and ECN through May 19, 2021.

Contents

Introduction.....	5
Terminology	5
Assertions	7
Test Requirements.....	20
<i>Hardware</i>	<i>20</i>
<i>Software</i>	<i>20</i>
Test Setups	21
<i>Host.....</i>	<i>21</i>
<i>Hub</i>	<i>23</i>
<i>Peripheral Device</i>	<i>25</i>
Tests	26
USB3 Tunneling.....	26
USB3 Adapter Layer	27
USB3 Mode Testing (Hubs and Devices Only)	55
TBT3 Mode Testing (Hubs and Devices Only)	56

Introduction

The tests defined in this test specification verify that a Router is compliant with Chapter 9 of the USB4™ Specification.

Note: This specification only covers USB3 Tunneling testing, it does not cover testing for native USB 3.2 support.

Note: If a USB4 Device, Hub or Dock includes an internal host controller, it also needs to pass xHCI CV testing over the PCIe tunnel using a TBT3 host.

Terminology

The following table describes the terms used in this document.

Analyzer	Test tool that captures and parses packets, transactions, ordered sets, etc.
Compliance Device	<p>A KG USB4 Device that is capable of performing Transport Layer Packet loopback.</p> <p>The KG USB4 Device is configured by USB4 CV (when USB4 CV is upstream of the UUT) or the Exerciser (when the exerciser is upstream of the UUT). Unless specified otherwise, the Compliance Device is configured as an ordinary KG USB4 Device. See the USB4 Connection Manager Guide for more information on how a USB4 Device is configured.</p> <p>The KG USB4 Device supports USB3 Tunneling at both USB 3.2 Gen 2x1 and USB 3.2 Gen 2x2 speeds.</p>
DFP	Downstream Facing Port.
Exerciser	The compliance test tool (hardware and software) that implements USB4 Port functionality and the behavior required for compliance testing.
IOP	Interop Testing. See USB4™ Interop Test Specification.
KG USB4 Device	“Known Good” USB4 Device. A USB4 Device that is known to be compliant with the USB4 Specification.
KG USB4 Host	“Known Good” USB4 Host. A USB4 Host that is known to be compliant with the USB4 Specification.
KG TBT3 Device	A Certified Thunderbolt™ 3 Device.
KG TBT3 Host	A Certified Thunderbolt™ 3 Host.
PUT	Port Under Test. The USB4 Port on a UUT that is the test point for compliance testing.
RUT	Router Under Test. The Router that is being tested for compliance.
UFP	Upstream Facing Port.
USB4 CV	Test tool that implements a Connection Manager with additional functionality to implement compliance tests.

USB4 Product	Refers to a USB4 host, USB4 hub, and/or USB4 device. Includes silicon, reference platforms, and end product.
UUT	Unit Under Test. The Router that is being tested for compliance.
VIF	Vendor Information File. File provided by UUT vendor that provides information about the characteristics and capabilities of the UUT.

Assertions

Compliance criteria are provided as a list of assertions that describe specific characteristics or behaviors that must be met. Each assertion provides a reference to the USB4 specification or other documents from which the assertion was derived. In addition, each assertion provides a reference to the specific test description(s) where the assertion is tested.

Each test assertion is formatted as follows:

Assertion #	Test #	Assertion Description
-------------	--------	-----------------------

Assertion#: Unique identifier for each spec requirement. The identifier is in the form USB4_SPEC_SECTION_NUMBER#X, where X is a unique integer for a requirement in that section.

Assertion Description: Specific requirement from the specification

Test #: A label for a specific test description in this specification that tests this requirement. Test # can have one of the following values:

NT	This item is not explicitly tested in a test description. Items can be labeled NT for several reasons – including items that are not testable, not important to test for interoperability, or are indirectly tested by other operations performed by the compliance test.
X.X	This item is covered by the test described in test description X.X in this specification.
IOP	This assertion is verified by the USB4 Interoperability Test Suite.

Test descriptions provide a high-level overview of the tests that are performed to check the compliance criteria. The descriptions are provided with enough detail so that a reader can understand what the test does. The descriptions do not describe the actual step-by-step procedure to perform the test.

The following Table presents the USB4 Specification Chapter 9 asserts.

Assertion #	Test	Assertion Description
9 USB3 Tunneling		
9#1	IOP	A USB4 host shall support USB3 tunneling.
9#2	TD 9.1	The Host Router in a USB4 host shall have one Downstream USB3 Adapter per Downstream Facing Port.
9#3	NT	Each Downstream USB3 Adapter shall interface to a downstream port on the host controller.
9#4	BT	A USB4 hub shall support USB3 tunneling.
9#5	TD 9.18	A USB4 hub shall incorporate an internal USB SuperSpeed Plus hub per the USB 3.2 Specification with the modifications defined in this chapter.
9#6	TD 9.1	The Device Router in a USB4 hub shall have an Upstream USB3 Adapter that interfaces with the upstream port of the internal USB 3.2 hub.
9#7	NT	The Device Router in a USB4 hub shall have for each Downstream Facing Port, a Downstream USB3 Adapter that interfaces to a downstream port on the internal USB 3.2 hub.
9#8	NT	A USB4 device that supports USB3 tunneling shall incorporate either an internal USB SuperSpeed Plus hub or an internal USB peripheral device per the USB 3.2 Specification with the modifications defined in this chapter.
9#9	TD 9.1	The Device Router in a USB4 device that supports USB3 tunneling shall have an Upstream USB3 Adapter that interfaces to the upstream port of the internal USB 3.2 peripheral device or internal USB 3.2 hub.
9.1 USB3 Adapter Layer		
9.1.1 Encapsulation		
9.1.1#1	TD 9.2	An LFPS event, a Ordered Set, a Link Command, a Link Management Packet, a Transaction Packet, and an Isochronous Timestamp Packet shall each be encapsulated into a single separate Tunneled Packet.
9.1.1#2	TD 9.8	A Data Packet shall be encapsulated into one or more Tunneled Packets. A Tunneled Packet shall not contain data from more than one Data Packet.
9.1.1#3	NT	Idle Symbols shall be discarded by a USB3 Adapter Layer.
9.1.1#4	TD 9.2 TD 9.3 TD 9.4 TD 9.5	The byte and bit ordering of an LFPS within a Tunneled Packet shall be as described in Section 9.1.1.1.

9.1.1#5	TD 9.2 TD 9.6	The byte and bit ordering of an Ordered Set within a Tunneled Packet shall be as described in Section 9.1.1.2.
9.1.1#6	TD 9.2	The bytes and bits in a Tunneled Packet payload, other than LFPS and Ordered Sets, shall be packed in the same order as the original USB3 construct, including the USB3 framing symbols.
9.1.1#7	TD 9.7	A USB3 Adapter shall not discard a Tunneled Packet due to lack of credits in the USB4 Fabric.
9.1.1#8	TD 9.7	When insufficient credits are available, the Router shall queue the Tunneled Packet and shall transport it once sufficient credits are available.
9.1.1#9	TD 9.2 TD 9.8	Table 9-1 defines the PDF values that shall be used for each type of USB construct.
9.1.1#10	NT	If a USB3 Adapter receives a Tunneled Packet with a PDF value other than 0 to 6, it shall discard the Tunneled Packet and shall not send any Packets in response.
9.1.1.1 LFPS Encapsulation		
9.1.1.1#1	TD 9.2 TD 9.3 TD 9.4 TD 9.5	An LFPS Tunneled Packet shall contain a single Doubleword of payload as defined in Table 9-2.
9.1.1.1#2	TD 9.2 TD 9.3 TD 9.4 TD 9.5	An LFPS Tunneled Packet shall have the structure shown in Figure 9-1.
9.1.1.1#3	NT	An LFPS event that is not listed in Table 9-2 shall not be transferred to the Transport Layer.
9.1.1.1#4	TD 9.2 TD 9.3 TD 9.4 TD 9.5	A USB3 Adapter Layer shall set no more than one of bits [22:17] in an LFPS Tunneled Packet.
9.1.1.1.1 CRC		
9.1.1.1.1#1	NT	The <i>CRC</i> field shall cover bits [23:0] of payload.
9.1.1.1.1#2	NT	The <i>CRC</i> field shall be calculated as defined in Section 5.1.2.1.1, using the following bit order: Bit 7 to bit 0; Bit 15 to bit 8; Bit 23 to bit 16

9.1.1.1.1#3	NT	When a USB3 Adapter Layer receives an LFPS Tunneled Packet, it shall verify the <i>CRC</i> field value.
9.1.1.1.1#4	NT	After correcting an error, a Router shall continue on as if the error had never occurred.
9.1.1.1.1#5	NT	When an error is detected but not corrected, the packet with the error shall be dropped and no other action taken on its behalf.
9.1.1.1.2 Rx Term Enable		
9.1.1.1.2#1	TD 9.2	The USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer when the local value of Rx termination changes or when the Path Enable bit in the USB3 Adapter Configuration Capability changes from 0b to 1b.
9.1.1.1.2#2	TD 9.2	The LFPS Tunneled Packet shall be sent 3 times.
9.1.1.1.2#3	NT	A Router shall implement a mechanism that allows a USB3 Adapter Layer to indicate far-end receiver termination to the internal USB3 Device.
9.1.1.1.2#4	TD 9.2	A USB3 Adapter Layer shall indicate far-end termination to the internal USB3 device when all of the following are true: Path setup is complete (i.e. the <i>Path Enable</i> bit and the <i>Valid</i> bit in the USB3 Adapter Configuration Capability are both set to 1b); After Path Setup is complete, the USB3 Adapter Layer received an LFPS Tunneled Packet with the <i>Rx Term Enable</i> bit set to 1b and the USB3 Adapter Layer has not received any subsequent LFPS Tunneled Packets with the <i>Rx Term Enable</i> bit set to 0b.
9.1.1.1.2#5	BT	When a Router transitions to Sleep state, a USB3 Adapter Layer shall maintain the same indicator value as before entry to Sleep state.
9.1.1.1.2#6	BT	When the Router exits Sleep state, the USB3 Adapter Layer shall continue to maintain the indicator value until the <i>Valid</i> bit in USB3 Adapter Port Configuration Capability is set to 1b.
9.1.1.1.2#7	BT	After the <i>Valid</i> bit is set to 1b, the USB3 Adapter Layer shall set the indicator as defined above.
9.1.1.1.3 SCD1		
9.1.1.1.3#1	TD 9.2	The USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with the <i>SCD1</i> bit set to 1b when instructed to do so by the internal USB3 device.
9.1.1.1.3#2	TD 9.2	The LFPS Tunneled Packet shall be sent 3 times.
9.1.1.1.3#3	NT	A USB3 Adapter Layer that receives an LFPS Tunneled Packet from the Transport Layer with the <i>SCD1</i> bit set to 1b shall indicate reception of SCD1 to the internal USB3 device until it receives a Tunneled Packet with different contents.

9.1.1.1.4 SCD2		
9.1.1.1.4#1	TD 9.2	The USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with the <i>SCD2</i> bit set to 1b when instructed to do so by the internal USB3 device.
9.1.1.1.4#2	TD 9.2	The packet shall be sent 3 times.
9.1.1.1.4#3	NT	A USB3 Adapter Layer that receives an LFPS Tunneled Packet from the Transport Layer with the <i>SCD2</i> bit set to 1b shall indicate reception of SCD2 to the internal USB3 device until it receives a Tunneled Packet with different contents.
9.1.1.1.5 U2 Exit		
9.1.1.1.5#1	TD 9.3	The USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with the <i>U2 Exit</i> bit set to 1b when the internal USB3 device indicates a U2 Exit event.
9.1.1.1.5#2	TD 9.3	The packet shall be sent 3 times.
9.1.1.1.5#3	TD 9.3	A USB3 Adapter Layer that receives an LFPS Tunneled Packet from the Transport Layer with the <i>U2 Exit</i> bit set to 1b shall indicate reception of a U2 Exit LFPS to the internal USB3 device until it receives a Tunneled Packet with different contents.
9.1.1.1.6 U3 Wakeup		
9.1.1.1.6#1	TD 9.4	When the internal USB3 device indicates the start of a U3 Wakeup event and a USB3 Path is enabled, a USB3 Adapter Layer shall send 3 LFPS Tunneled Packets to the Transport Layer. Each LFPS Tunneled Packet shall have the <i>U3 Wakeup</i> bit set to 1b.
9.1.1.1.6#2	TD 9.4	If a USB3 Adapter Layer detects the beginning of a U3 Wakeup event before a USB3 Path is enabled, it shall ignore the USB3 Wakeup event and shall not send any LFPS Tunneled Packets for that event.
9.1.1.1.6#3	NT	A USB3 Adapter Layer that receives an LFPS Tunneled Packet from the Transport Layer with the <i>U3 Wakeup</i> bit set to 1b shall indicate reception of a U3 Wakeup LFPS to the internal USB3 device until it receives a Tunneled Packet with different contents.
9.1.1.1.7 Warm Reset		
9.1.1.1.7#1	NT	When Warm Reset is asserted by the internal USB3 device, the Downstream USB3 Adapter Layer shall: Discard any queued Tunneled Packets.
9.1.1.1.7#2	TD 9.5	When Warm Reset is asserted by the internal USB3 device, the Downstream USB3 Adapter Layer shall: Send an LFPS Tunneled Packet to the Transport Layer with the Warm Reset bit set to 1b.
9.1.1.1.7#3	TD 9.5	The LFPS Tunneled Packet shall be sent 3 times.

9.1.1.1.7#4	NT	While Warm Reset is active, a Downstream USB3 Adapter shall discard any Tunnel Packets it receives and clear any indication of LFPS reception towards the internal USB3 device.
9.1.1.1.7#5	NT	An Upstream USB3 Adapter Layer that receives an LFPS Tunneled Packet with the Warm Reset bit set to 1b shall indicate assertion of a Warm Reset to the internal USB3 device until it receives a Tunneled Packet with different contents.
9.1.1.1.7#6	TD 9.5	The Downstream USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with the Warm Reset bit set to 0b when Warm Reset is de-asserted by the internal USB3 device.
9.1.1.1.7#7	TD 9.5	The LFPS Tunneled Packet shall be sent 3 times.
9.1.1.1.7#8	NT	An Upstream USB3 Adapter Layer that receives an LFPS Tunneled Packet from the Transport Layer with the Warm Reset bit set to 0b shall indicate de-assertion of a Warm Reset to the internal USB3 device until it receives a Tunneled Packet with different contents.
9.1.1.1.7#9	NT	After Warm Reset is de-asserted, a USB3 Adapter Layer shall not forward any Ordered Sets, packets, or events to the internal USB3 device that were received before or during Warm Reset assertion.
9.1.1.1.8 LBPM		
9.1.1.1.8#1	TD 9.2	The USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with the <i>LBPM Enable</i> bit set to 1b when instructed to do so by the internal USB3 device.
9.1.1.1.8#2	TD 9.2	The LBPM field shall contain the USB3 LBPM construct. Bits[7:0] of the USB3 LBPM are mapped to Bits[7:0] of the LBPM field, respectively.
9.1.1.1.8#3	TD 9.2	The LFPS Tunneled Packet shall be sent 3 times.
9.1.1.1.8#4	NT	A USB3 Adapter Layer that receives an LFPS Tunneled Packet with the <i>LBPM Enable</i> bit set to 1b shall do the following until it receives a Tunneled Packet with different contents: Indicate reception of LBPM to the internal USB3 device.
9.1.1.1.8#5	NT	A USB3 Adapter Layer that receives an LFPS Tunneled Packet with the <i>LBPM Enable</i> bit set to 1b shall do the following until it receives a Tunneled Packet with different contents: Communicate the value in the <i>LBPM</i> field to the internal USB3 device.
9.1.1.1.9 LFPS Stop		
9.1.1.1.9#1	TD 9.4	A USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with bits [22:17] equal 00h for the following cases: The Internal USB3 device indicates no LFPS Response Timeout for U3 Exit

9.1.1.1.9#2	TD 9.5	A USB3 Adapter Layer shall send an LFPS Tunneled Packet to the Transport Layer with bits [22:17] equal 00h for the following cases: The Internal USB3 device indicates Warm Reset done
9.1.1.1.9#3	TD 9.4 TD 9.5	The LFPS Tunneled Packet shall be sent 3 times.
9.1.1.2 Ordered Set Encapsulation		
9.1.1.2#1	TD 9.2 TD 9.6	An Ordered Set Tunneled Packet shall have the single Doubleword payload defined in Table 9-3.
9.1.1.2#2	TD 9.2 TD 9.6	An Ordered Set Tunneled Packet shall have the structure shown in Figure 9-2.
9.1.1.2#3	TD 9.2 TD 9.6	A USB3 Adapter Layer shall set one and no more than one of bits [2:0] in an Ordered Set Tunneled Packet.
9.1.1.2#4	TD 9.2 TD 9.6	TS1 or TS2 Ordered Sets shall contain the USB3 Link Functionality construct. Bits[7:0] of the USB3 Link Functionality are mapped to Bits[7:0] of the Link Functionality field, respectively. TSEQ Ordered Set – set to 00h by the USB3 Adapter Layer. SDS Ordered Set – set to 00h by the USB3 Adapter Layer.
9.1.1.2#5	TD 9.2 TD 9.6	When a USB3 Adapter Layer receives a TSEQ, TS1, TS2, or SDS Ordered Set from the internal USB3 device that is not identical to the previous Ordered Set received from the internal USB3 device, it shall send 3 copies of an Ordered Set Tunneled Packet to the Transport Layer, with the respective fields set per Table 9-3.
9.1.1.2#6	NT	All other Ordered Sets received from the internal USB3 device shall be discarded by the USB3 Adapter Layer and shall not cause an Ordered Set Tunneled Packet to be sent to the Transport Layer.
9.1.1.2#7	NT	A USB3 Adapter Layer shall only send Ordered Sets that target Lane 0 to the Transport Layer.
9.1.1.2#8	NT	A USB3 Adapter Layer shall discard Ordered Sets that target a non-zero Lane so that they are not sent over the USB4 Fabric.
9.1.1.2#9	NT	When a USB3 Adapter Layer receives an Ordered Set Tunneled Packet, it shall verify the <i>CRC</i> field value.
9.1.1.2#10	NT	When an error is detected but not corrected, the packet with the error shall be dropped and no other action taken on its behalf.
9.1.1.2#11	IOP	After verifying the <i>CRC</i> field value: If the <i>TS1</i> bit in the received Ordered Set Tunneled Packet is set to 1b, the USB3 Adapter Layer shall indicate reception of TS1 Ordered Set to the internal USB3 device.

9.1.1.2#12	IOP	After verifying the <i>CRC</i> field value: If the <i>TS2</i> bit in the received Ordered Set Tunneled Packet is set to 1b, the USB3 Adapter Layer shall indicate reception of <i>TS2</i> Ordered Set to the internal USB3 device.
9.1.1.2#13	IOP	After verifying the <i>CRC</i> field value: If the <i>SDS</i> bit in the received Ordered Set Tunneled Packet is set to 1b, a USB3 Adapter Layer shall indicate reception of <i>SDS</i> Ordered Set to the internal USB3 device.
9.1.1.3 Link Command Encapsulation		
9.1.1.3#1	IOP	A USB3 Adapter Layer that receives a Link Command from the internal USB3 device shall send a Link Command Tunneled Packet to the Transport Layer with a 2-Doubleword payload.
9.1.1.3#2	IOP	The Link Command Tunneled Packet payload shall contain the Link Command.
9.1.1.3#3	NT	Upon receiving a Link Command Tunneled Packet from the Transport Layer, a USB3 Adapter Layer shall transfer the Link Command Tunneled Packet to the internal USB Port.
9.1.1.4 Idle Symbols		
9.1.1.4#1	NT	A USB3 Adapter Layer shall drop any Idle Symbols received from the internal USB3 device.
9.1.1.5 LMP Encapsulation		
9.1.1.5#1	IOP	A USB3 Adapter Layer that receives a USB3 Link Management Packet (LMP) from the internal USB3 device shall send an LMP Tunneled Packet to the Transport Layer with a 5 Doubleword payload.
9.1.1.5#2	IOP	The LMP Tunneled Packet payload shall contain the framed LMP.
9.1.1.5#3	NT	Upon receiving an LMP Tunneled Packet from the Transport Layer, a USB3 Adapter Layer shall transfer the LMP to the internal USB device.
9.1.1.6 TP Encapsulation		
9.1.1.6#1	IOP	A USB3 Adapter Layer that receives a USB3 Transaction Packet (TP) from the internal USB3 device shall send a TP Tunneled Packet to the Transport Layer with a 5 Doubleword payload.
9.1.1.6#2	IOP	The TP Tunneled Packet payload shall contain the framed TP.
9.1.1.6#3		If the USB3 Adapter Layer receives a Deferred DPH from the internal USB3 device, it shall send a TP Tunneled Packet to the Transport Layer with a 5 Doubleword payload.
9.1.1.6#4		The payload shall contain the Deferred DPH and its USB3 framing symbols.

9.1.1.6#5	NT	Upon receiving a TP Tunneled Packet from the Transport Layer, a USB3 Adapter Layer shall transfer the TP to the internal USB3 device.
9.1.1.7 ITP Encapsulation		
9.1.1.7#1	NT	A Downstream USB3 Adapter Layer that receives an Isochronous Timestamp Packet (ITP) from the internal USB3 device shall: set the TMU Time Capture field to the nanosecond portion of the current Host Router Time (t_g).
9.1.1.7#2	TD 9.10	A Downstream USB3 Adapter Layer that receives an Isochronous Timestamp Packet (ITP) from the internal USB3 device shall: send an ITP Tunneled Packet with the format defined in Figure 9-4 to the Transport Layer.
9.1.1.7#3	TD 9.10	An Upstream USB3 Adapter Layer that receives an ITP Tunneled Packet from the Transport Layer shall: Update the Delta field of the ITP according to the formula below: Updated Delta = Delta + (Host Router time Nanosecond – TMU Time Capture) / $t_{IsochTimeStampGranularity}$
9.1.1.7#4	TD 9.10	A USB3 Adapter Layer shall meet the required accuracy of the <i>Delta</i> field in the ITP as defined by Section 8.7 of the USB 3.2 Specification.
9.1.1.7#5	NT	An Upstream USB3 Adapter Layer that receives an ITP Tunneled Packet from the Transport Layer shall: Update the <i>CRC-16</i> field in the ITP.
9.1.1.7#6	NT	An Upstream USB3 Adapter Layer that receives an ITP Tunneled Packet from the Transport Layer shall: Forward the ITP to the internal USB device.
9.1.1.7#7	TD 9.10	If the Time Disruption bit is set to 1b in Router Configuration Space, an Upstream USB3 Adapter Layer shall set the Delayed bit in the Link Control Word to 1b.
9.1.1.7#8	NT	A USB3 Adapter Layer shall recalculate the CRC5 field within the Link Control Word if it modified the Delayed bit.
9.1.1.8 Data Packet (DP) Encapsulation		
9.1.1.8#1	TD 9.8	If the size of a USB3 Data Packet is 252 bytes or less, then the USB3 Adapter Layer shall send a single Tunneled Packet of type Start DP Segment to the Transport Layer.
9.1.1.8#2	TD 9.8	The Tunneled Packet shall carry the unsegmented USB3 Data Packet as payload and any padding needed for DW alignment.
9.1.1.8#3	TD 9.8	If the size of a USB3 Data Packet is larger than 252 bytes, the USB3 Data Packet shall be segmented into multiple Tunneled Packets as shown in Figure 9-6.
9.1.1.8#4	TD 9.8	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: All Tunneled Packets with the possible exception of the last packet shall include 252 bytes of payload.

9.1.1.8#5	TD 9.8	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: The first Tunneled Packet shall be of type Start DP Segment.
9.1.1.8#6	TD 9.8	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: Any following Tunneled Packets other than the last Tunneled Packet shall be of type Middle DP Segment.
9.1.1.8#7	TD 9.7	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: The last Tunneled Packet shall be of type End DP Segment.
9.1.1.8#8	TD 9.7	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: The last Tunneled Packet shall pad the payload to be Doubleword aligned.
9.1.1.8#9	TD 9.7	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: The last Tunneled Packet shall have payload size that does not exceed 252 bytes.
9.1.1.8#10	NT	When a USB3 Adapter Layer segments a USB3 Data Packet into Multiple Tunneled Packets, it shall follow the rules: The Tunneled Packets shall be sent to the Transport layer such that the byte ordering of the original USB3 Data Packet is maintained.
9.1.1.8#11	TD 9.9	When re-assembling Tunneled Packets into USB3 Data Packets, the USB3 Adapter Layer shall: Drop a Tunneled Packet of type Middle DP Segment that comes immediately after a Tunneled Packet of type End DP Segment.
9.1.1.8#12	TD 9.9	When re-assembling Tunneled Packets into USB3 Data Packets, the USB3 Adapter Layer shall: Drop a Tunneled Packet of type End DP Segment that comes immediately after a Tunneled Packet of type End DP Segment.
9.1.1.8#13	TD 9.9	When re-assembling Tunneled Packets into USB Data Packets, the USB3 Adapter Layer shall: Nullify or partially nullify a USB3 Data Packet when both of the following are true: A Tunneled packet of type Start DP Segment is received and the length information in the USB3 DPH indicates it does not fit into a single Tunneled Packet; A Tunneled Packet of type End DP Segment is not received within tReassemble from the reception of the Tunneled Packet of type Start DP Segment.
9.1.2 Bandwidth Negotiation		
9.1.2#1	TD 9.11	When the <i>Host Controller Ack</i> field = 0: The value in the <i>Consumed Upstream Bandwidth</i> field shall not exceed the value in the <i>Allocated Upstream Bandwidth</i> field.
9.1.2#2	TD 9.12	When the <i>Host Controller Ack</i> field = 0: The value in the <i>Consumed Downstream Bandwidth</i> field shall not exceed the value in the <i>Allocated Downstream Bandwidth</i> field.

9.1.2#3	NT	When the <i>Host Controller Ack</i> field = 1: The internal host controller shall not read the <i>Allocated Upstream Bandwidth</i> or <i>Allocated Downstream Bandwidth</i> fields
9.1.2#4	NT	When the <i>Host Controller Ack</i> field = 1: The internal host controller shall not update <i>Consumed Upstream Bandwidth</i> or <i>Consumed Downstream Bandwidth</i> fields.
9.1.2#5	TD 9.11 TD 9.12	The internal host controller shall negotiate bandwidth as shown in Figure 9-7.
9.1.2#6	TD 9.2	When the USB3 link reaches U0, a USB3 Adapter Layer shall: Set the <i>Actual Link Rate</i> field to indicate the established link rate.
9.1.2#7	TD 9.2	When the USB3 link reaches U0, a USB3 Adapter Layer shall: Set the <i>USB3 Link Valid</i> field to 1b.
9.1.2#8	TD 9.3 TD 9.4	When the USB3 link is not in U0, Recovery, U2 or U3, a USB3 Adapter Layer shall set the <i>USB3 Link Valid</i> field to 0b.
9.1.3 Timing Parameters		
9.1.3#1	TD 9.9	Time between Tunneled Packets which is used to determine loss of a USB3 Data Packet segment.
9.2 Internal USB3 Device		
9.3#1	NT	A USB3 Physical Layer is not needed in a USB3 port that interfaces with a USB3 Adapter. Therefore, Physical Layer scrambling is not performed, regardless of the value of the Disable Scrambling bit in a received TS Ordered Set.
9.2.1 Link Layer		
9.3.1#1	IOP	An internal USB3 device port that interfaces to a USB3 Adapter Layer shall implement a USB Link Layer as defined in the USB 3.2 Specification with the modifications, configurations, and parameters described in this section.
9.3.1#2	TD 9.2	The Link Layer shall support Gen 2 single-Lane (2x1) and may support Gen 2 dual-Lane (2x2).
9.3.1#3	NT	No other Link capabilities shall be supported.
9.3.1#4	TD 9.2	An Internal USB3 device shall not send a LBPM PHY Capability with a value of 0 in bits [3:2].
9.2.1.1 Link Training and Status State Machine (LTSSM)		
9.3.1.1#1	NT	The Link Layer shall implement a Link Training and Status State Machine (LTSSM) with the following adjustments: Loopback state shall not be supported.

9.3.1.1#2	NT	The Link Layer shall implement a Link Training and Status State Machine (LTSSM) with the following adjustments: Compliance Mode state shall not be supported.
9.3.1.1#3	NT	The Link Layer shall implement a Link Training and Status State Machine (LTSSM) with the following adjustments: U1 state shall not be supported.
9.3.1.1#4	NT	The Link Layer shall implement a Link Training and Status State Machine (LTSSM) with the following adjustments: When the LTSSM of an Upstream Facing Port is in Disabled state, it shall unconditionally transition to the Rx.Detect state.
9.3.1.1#5	BT	The Link Layer shall implement a Link Training and Status State Machine (LTSSM) with the following adjustments: TS1 and TS2 shall not be scrambled.
9.2.1.2 Timers and Timeouts		
9.2.1.2#1	TD 9.14 TD 9.15 TD 9.16	An internal USB3 device shall use the parameter values in Table 9-4.
9.2.2 USB3 Protocol Layer		
9.3.2#1	NT	The internal USB3 device shall implement a Protocol Layer as defined in the USB3.2 Specification with the following adjustments: LDM Protocol shall not be supported over ports that interfaces a USB3 Adapter
9.2.3 Descriptors		
9.3.3#1	IOP	The internal USB3 device shall implement Descriptors as defined in the USB 3.2 Specification with the following adjustments: If a Router supports entering CL1 or CL2 when the USB3 link between the USB3 Adapter and the internal USB3 device is in U2 state, then the value for wU2DevExitLat shall include the maximum sum of the Router enter and exit time from the supported CLx.
9.3 Paths		
9.4#1	NT	A USB3 Adapter Layer shall put HopID=8 in the header of an outgoing Tunneled Packet before handing it off to the Transport Layer for routing.
9.3.1 Path Setup		
9.3.2 Path Teardown		
9.3.2#1	TD 9.13	When a Router detects a disconnect on a Downstream Facing Port, it shall set the Path Enable bit to 0b in the USB3 Adapter Configuration Capability of the corresponding USB3 Adapter.

9.3.2#2	TD 9.13	When the Path Enable bit is set to 0b and the Valid bit is set to 1b in the USB3 Adapter Configuration Capability the USB3 Adapter Layer shall: Not issue any Tunneled Packets to the Transport Layer
9.3.2#3	NT	When the Path Enable bit is set to 0b and the Valid bit is set to 1b in the USB3 Adapter Configuration Capability the USB3 Adapter Layer shall: Remove far-end receiver termination to the internal USB3 device as defined in Section 9.1.1.1.2.
9.3.2#4	IOP	The internal USB3 device port shall detect a disconnect within 500ms.

Test Requirements

Hardware

The following test equipment is needed to perform the tests in this specification:

- KG USB4 Host (1)
- USB4 Compliance Device (2)
- USB4 Analyzer (1)
- USB4 Exerciser (1)
- KG USB 3.2 device (1)

Software

The following software tools are needed to perform the tests in this specification:

- USB4 CV

Test Setups

This section defines the test setups for a Router that is part of a USB4™ host, hub, or device.

Note: A USB4-Based Dock is tested as a USB4 hub.


Host

This section defines the test setups for a Host Router. The Port Under Test (PUT) is highlighted in each figure.

AN_HOST_DFP1—USB3_01

Description:


- The UFP of the Compliance Device is connected to the DFP of the UUT.
- The USB4 Analyzer is connected between the UUT and the Compliance Device.



EX_HOST_DFP1—USB3_02

Description:

- The Exerciser is connected to the DFP of the UUT.
- Unless specified otherwise, the Exerciser is in USB4 device mode and presents as UFP.




Hub

This section describes the test setups for a Hub Router (i.e. a Device Router with one or more DFP). The Port Under Test (PUT) is highlighted in each figure.

AN_HUB_UFP1—USB3_01

Description:


- The DFP on the KG USB4 Host connects to the UFP of the UUT.
- The Analyzer is connected between the KG USB4 Host and the UUT.



EX_HUB_UFP1—USB3_02

Description:


- The Exerciser connects to the UFP of the UUT.
- The Exerciser is in USB4 Host mode and presents as DFP.



AN_HUB_DFP1—USB3_03

Description:


- DFP on KG USB4 Host connects to UFP of the UUT.
- UFP of Compliance Device connects to DFP of the UUT.
- Analyzer is connected between the UUT and Compliance Device.



EX_HUB_DFP1—USB3_04

Description:

- DFP on KG USB4 Host connects to UFP of the UUT.
- The Exerciser connects to DFP of the UUT.
- The Exerciser is in USB4 Device mode and presents as UFP.



Note: Unless specified otherwise, the xHCI CV driver is used as the Host Controller Driver.


Peripheral Device

This section describes the test setups for a Peripheral Device Router (i.e. a Device Router that does not have any DFP). The Port Under Test (PUT) is highlighted in each figure.

AN_DEV_UFP1—USB3_01

Description:


- The DFP on the KG USB4 Host connects to the UFP of the UUT.
- The Analyzer is connected between the KG USB4 Host and the UUT.



EX_DEV_UFP1—USB3_02

Description:

- The Exerciser connects to the UFP of the UUT.
- The Exerciser is in USB4 Host mode and presents as DFP.



Tests

Unless specified otherwise, the tests in this section are repeated on each Port on the UUT.

Unless specified otherwise, a test will timeout if it takes more than 1 second to go from one step to the next step. It is a test failure if a test step times out.

For a USB4 Hub, The tests in this section are repeated with the following configurations:

- The Link on the UFP and the DFP are USB4
- The Link on the UFP is USB4 and the Link on the DFP is USB 3.2

USB3 Tunneling

TD 9.1 USB3 Adapter Scan Test

Note: This test is only performed once on the UUT.

- A. Purpose:
 - For USB4 hosts and hubs, verify that there is one Downstream USB3 Adapter for each USB4 Downstream facing port
 - For USB4 hubs and devices, verify that there is one Upstream USB3 Adapter
- B. Asserts:
 - 9#4, 9#8, 9#11
- C. Setup:
 - AN_HOST_DFP1—USB3_01 (Host)
 - AN_HUB_UFP1—USB3_01 (Hub UFP)
 - AN_HUB_DFP1—USB3_03 (Hub DFP)
 - AN_DEV_UFP1—USB3_01 (Peripheral Device)
- D. Procedure:
 1. USB4 CV scans all the USB3 Adapters in the UUT
 2. USB4 CV verifies that the number of the Downstream USB3 Adapters is equal to the number of the Downstream USB4 ports on the UUT
 3. If UUT is a USB4 Hub or Peripheral Device, USB4 CV verifies that the UUT has one Upstream USB3 Adapter

USB3 Adapter Layer

TD 9.2 Link Initialization Test

- A. Purpose:
 - Verify that the UUT performs USB3 Tunnel link initialization correctly
- B. Asserts:
 - 9.1.1#1
- C. Setup:
 - AN_HOST_DFP1—USB3_01 (Host)
 - AN_HUB_UFP1—USB3_01 (Hub UFP)
 - AN_HUB_DFP1—USB3_03 (Hub DFP)
 - AN_DEV_UFP1—USB3_01 (Peripheral Device)
- D. Procedure:
 1. USB4 CV enumerates the USB4 topology according to the CM Guide
 2. USB4 CV performs USB3 Path setup according to the USB4 specification and CM Guide

Part 1 – LFPS Handshake

3. During Part 1 USB4 CV verifies that:
 - a. PUT sends LFPS Packets with the format according to Figure 9-1 in the USB4 specification
 - b. PUT sends at least 3 LFPS Packets
 - c. The PDF field in each LFPS Packet is set to 0
4. USB4 CV verifies that the PUT sends LFPS Packets with:
 - a. term_en field set to 1
 - b. All the other fields set to 0
5. KG Router responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. All the other fields set to 0
6. USB4 CV verifies that the PUT responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. SCD1 field set to 1
 - c. All the other fields set to 0
7. KG Router responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. SCD1 field et to 1
 - c. All the other fields set to 0
8. USB4 CV verifies that the PUT responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. SCD2 field set to 1
 - c. All the other fields set to 0
9. KG Router responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. SCD2 field set to 1
 - c. All the other fields set to 0
10. USB4 CV verifies that the PUT responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. LBMP Enable field set to 1
 - c. LBMP field type equal to PHY Capability
 - d. LBPM field subtype not equal to 0
 - e. All the other fields set to 0

11. KG Router responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. LBMP Enable field set to 1
 - c. LBMP field type equal to PHY Capability
 - d. LBPM field subtype equal to highest support capability
 - e. All the other fields set to 0
12. USB4 CV verifies that the PUT responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. LBMP Enable field set to 1
 - c. LBMP field type equal to PHY Ready
 - d. LBPM field subtype equal to highest support capability
 - e. All the other fields set to 0
13. KG Router responds with LFPS Packets with:
 - a. term_en field set to 1
 - b. LBMP Enable field set to 1
 - c. LBMP field type equal to PHY Ready
 - d. LBPM field subtype equal to highest support capability
 - e. All the other fields set to 0

Part 2 – Ordered Set handshake

14. During Part 2 USB4 CV verifies:
 - a. PUT sends Ordered Set Packets with the format according to figure 9-2 in the USB4 specification
 - b. PUT sends least 3 Ordered Set Packets
 - c. The PDF field in each Ordered Set Packet is set to 1
15. USB4 CV verifies that the PUT sends Order Set Packets with:
 - a. TS1 field set to 1
 - b. All the other fields set to 0 except bit 3 in the link functionality that must be set on the last 3 packets.
16. KG Router responds with Ordered Set Packets with:
 - a. TS1 field set to 1
 - b. All the other fields set to 0 except bit 3 in the link functionality that must be set on the last 3 packets.
17. USB4 CV verifies that the PUT sends Order Set packet with:
 - a. TS2 field is set to 1
 - b. All the other fields set to 0 except bit 3 in the Link Functionality field
18. KG Router responds with Ordered Set Packets with:
 - a. TS2 field set to 1
 - b. All the other fields set to 0 except bit 3 in the Link Functionality field
19. USB4 CV verifies that the PUT sends Order Set Packets with:
 - a. SDS field set to 1
 - b. All the other fields set to 0
20. KG Router responds with Ordered Set Packets with:
 - a. SDS field set to 1
 - b. All the other fields set to 0

Part 3 – Link in U0

21. During Part 3 USB4 CV verifies the following for each USB3 Tunneled Packet:
 - a. The PDF is between 2 and 6 (inclusive)
22. USB4 CV verifies that the PUT follows the link initialization sequences according to USB3.2 specification section 7.2.4.1.1 Initialization
23. USB4 CV verifies that the PUT stays in U0 at least 1 sec

24. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
25. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 is set and the *PLS* field value is 0h

TD 9.3 U2 Enter and Exit Test

A. Purpose

- Verify that the PUT can enter and exit from U2

B. Asserts:

- 9.1.1.1.5#1#2

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_UFP1—USB3_01 (Hub UFP)
- AN_HUB_DFP1—USB3_03 (Hub DFP)
- AN_DEV_UFP1—USB3_01 (Peripheral Device)

D. Procedure:

UUT is a USB4 Host

Part 1 – Entry to U2

1. Perform link initialization according to TD 9.2
2. USB4 CV enables U2 in the Compliance Device and in the UUT

Note: The xHCI driver initiates the transition to U2 as follows:

 1. The xHCI driver writes the U2 Timeout value in the PORTPMSC register
 2. The xHCI driver sends a U2 enable command to the device
3. USB4 CV verifies that the PUT either requests or accepts entry to U2
4. USB4 CV verifies that there are no USB3 Tunneled Packets for 1 sec after the PUT enters U2 state
5. USB4 CV verifies that the Actual Link Rate field in ADP_USB_CS_4 is equal to the minimum between Maximum Supported Link Rate field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
6. USB4 CV verifies that the USB Link Valid field in ADP_USB_CS_4 in the UUT and in the Compliance Device is set and the PLS field value is 2h

Part 2 – Exit U2 from the UUT

7. USB4 CV initiates exit from U2 from the UUT by writing 0x0 to U2 Timeout in PORTPMSC register in the xHCI interface
8. USB4 CV verifies that the UUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
9. The Compliance Device responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
10. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

Part 3 – Exit U2 from the Compliance Device

11. USB4 CV initiates U2 entry according to Part 1

12. Initiate U2 exit request from the Compliance Device as follows:
 - a. Wake from the device if possible
 - b. If wake from the device is not possible, Analyzer initiates U2 exit
13. USB4 CV verifies that the UUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
14. The Compliance Device responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
15. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

UUT is a USB4 Peripheral Device

Part 1 – Entry to U2

1. Perform link initialization according to TD 9.2
2. USB4 CV enables U2 in the PUT
3. USB4 CV verifies that the PUT requests entry to U2
4. USB4 CV enables U2 in the USB4 Host Router
5. USB4 CV verifies that the PUT accepts entry to U2
6. USB4 CV verifies that there are no USB3 Tunneled Packets for 1 sec after the PUT enters U2 state
7. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
8. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the UUT and in the KG USB4 Host is set and the *PLS* field value is 2h

Part 2 – Exit U2 from the KG USB4 Host

9. USB4 CV initiates exit from U2 from the KG USB4 Host by writing 0x0 to U2 Timeout in PORTPMSC register in the xHCI interface
10. The KG USB4 Host sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
11. USB4 CV verifies that the UUT responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
12. USB4 CV verifies Link Initialization according to Part 2 and Part 3 in TD 9.2

Part 3 – Exit U2 from the UUT

Note: Only perform Part 3 if wake from the UUT is supported

13. Perform U2 entry according to Part 1
14. Perform wake from the UUT
15. USB4 CV verifies that the UUT sends at least 3 LFPS Packets with:

- a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
16. The KG USB4 Host responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
17. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

UUT is a USB4 Hub (UFP)

Note: PUT is the Upstream Facing Port of the UUT

Parts 1 through 3 are repeated with:

- All downstream ports disconnected
- All downstream ports connected and in U2
- All downstream ports connected and in U3
- If the UUT has more than 2 two downstream ports:
 - One downstream ports disconnected
 - One downstream ports connected and in U2
 - One downstream ports connected and in U3

Part 1 – Entry to U2

1. Perform link initialization according to TD 9.2
2. USB4 CV enables U2 in the PUT
3. USB4 CV verifies that the PUT requests entry to U2
4. USB4 CV enables U2 in the USB4 Host Router
5. USB4 CV verifies that the PUT accepts entry to U2
6. USB4 CV verifies that there are no USB3 Tunneled Packets for 1 sec after the PUT enters U2 state
7. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
8. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the UUT and in the KG USB4 Host is set and the *PLS* field value is 2h

Part 2 – Exit U2 from the USB4 KG Host

9. USB4 CV initiates exit from U2 from the USB4 KG Host by writing to 0x0 to U2 Timeout in PORTPMSC register in the xHCI interface
10. USB4 CV verifies that the USB4 KG Host sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
11. USB4 CV verifies that the UUT responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1

- c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 12. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2
- 13. USB4 CV verifies that all connected downstream ports return to U0

Part 3 – Exit U2 from the UUT

- 14. Perform U2 entry according to Part 1
- 15. Perform wake from the UUT by:
 - a. Disconnect on each DFP
 - b. Connect on each DFP
 - c. Wake from the Compliance Device connected to each DFP
- 16. USB4 CV verifies that the UUT send at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 17. USB4 CV verifies that the USB4 KG Host responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 18. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2
- 19. USB4 CV verifies that all connected downstream ports return to U0

UFP is a USB4 Hub (DFP):

Note: PUT is the Downstream Facing Port of the UUT

Part 1 – Entry to U2

- 1. Perform link initialization on the UFP of the UUT and on the PUT according to TD 9.2
- 2. USB4 CV enables U2 in the PUT on the UUT
- 3. USB4 CV verifies that the PUT requests entry to U2
- 4. USB4 CV enables U2 in the Compliance Device that connected to the PUT
- 5. USB4 CV verifies that the PUT accepts entry to U2
- 6. USB4 CV verifies there are no USB3 Tunneled Packets for 1 sec after the PUT enters U2 state
- 7. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
- 8. USB4 CV verifies that *USB Link Valid* field in ADP_USB_CS_4 in the PUT and in the Compliance Device is set and the *PLS* field value is 2h

Part 2– Exit U2 from the Compliance Device

- 9. Compliance Device requests wake from U2 by issuing a wake
- 10. Compliance Device sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 11. USB4 CV verifies that the PUT responds with at least 3 LFPS Packets with:
 - a. PDF set to 0

- b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 12. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2
- 13. USB4 CV verifies that all connected ports return to U0

Part 3 – Exit U2 from the PUT

- 14. USB4 CV performs wake to the PUT as follows:
 - a. Disable U2 in the port features
 - b. Send data to the Compliance Device that connected to the PUT
- 15. USB4 CV verifies that the PUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 16. USB4 CV verifies that the Compliance Device responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U2 exit bit field set to 1
 - d. All other fields set to 0
- 17. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2
- 18. USB4 CV verifies that all connected ports return to U0

A. Purpose

- Verify that the PUT can enter and exit from U3
- Verify that the PUT can handle U3 timeout

B. Asserts:

- 9.1.1.1.6#1, 9.1.1.1.6#2, 9.1.1.1.6#4, 9.1.1.1.6#6

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_UFP1—USB3_01 (Hub UFP)
- AN_HUB_DFP1—USB3_03 (Hub DFP)
- AN_DEV_UFP1—USB3_01 (Peripheral Device)

D. Procedure:

UUT is a USB4 Host or USB4 Peripheral Device

Part 1 – Entry to U3

1. Perform link initialization according to TD 9.2
2. USB4 CV requests entry to U3 in the USB4 Host
3. USB4 CV verifies that the USB4 Host requests entry to U3
4. USB4 CV verifies that the USB4 Device accepts entry to U3
5. USB4 CV verifies there are no USB3 Tunneled Packets for 1 sec after entering to U3
6. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
7. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the UUT is set and the *PLS* field value is 3h

Part 2 – Exit U3 from the USB4 Host

8. Initiate U3 entry according to Part 1
9. Transition the system to S3 state
10. Perform system resume
11. USB4 CV enumerates the USB4 Device and the USB4 Host but does not set up a USB3 Path
12. USB4 CV Initiates exit from U3 from the USB4 Host by writing to PORTSC in the xHCI interface
13. USB4 CV verifies that there are no USB3 Tunneled Packets
14. USB4 CV sets up a USB3 Path
15. USB4 CV verifies that the USB4 Host sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
16. USB4 CV verifies that the USB4 Device responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
17. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

Part 3 – Exit U3 from the USB4 Device

18. Initiate U3 entry according to Part 1
19. Transition the system to S3 state
20. Perform wake from the KG USB4 Device
21. USB4 CV enumerates the USB4 Device and the USB4 Host, but does not set up a USB3 Path
22. USB4 CV verifies that there are no USB3 Tunneled Packets for 5 sec
23. USB4 CV sets up a USB3 Path
24. USB4 CV verifies that the USB4 Device sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
25. USB4 CV writes to PORTSC in the xHCI interface back to U0
26. USB4 CV verifies that the USB4 Host responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
27. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2.

Part 4 – Exit U3 from the USB4 Device with Retry

28. Initiate U3 entry according to Part 1
29. Perform wake from the KG USB4 Device
30. USB4 CV verifies that the USB4 Device sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
31. Analyzer wait 10ms and verify that the USB4 Device sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 0
 - d. All other fields set to 0
32. Analyzer wait 100ms and verify that the USB4 Device sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
33. USB4 CV writes to PORTSC in the xHCI interface back to U0
34. USB4 CV verifies that the USB4 Host responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
35. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

UUT is USB4 Hub (UFP)

Note: PUT is the Upstream Facing Port of the UUT

Parts 1 through 4 are repeated with:

- All downstream ports disconnected
- All downstream ports connected and in U2
- All downstream ports connected and in U3
- If the UUT has more than 2 two downstream ports:
 - One downstream ports disconnected
 - One downstream ports connected and in U2
 - One downstream ports connected and in U3

Part 1 – Entry to U3

1. Perform link initialization according to TD 9.2
2. USB4 CV transitions all of the downstream ports to U3
3. Initiate U3 entry for the upstream port of the UUT according to Part 1

Part 2 – Exit U3 from the KG USB4 Host

4. USB4 CV initiates exit from U3 from the KG USB4 Host by writing to PORTCS register in the xHCI interface
5. USB4 CV verifies that the KG USB4 Host sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields are set to 0
6. USB4 CV verifies that the UUT responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields are set to 0
7. USB4 CV verifies link initialization of the UUT upstream port according to Part 2 and Part 3 in TD 9.2
8. USB4 CV verifies that all connected downstream ports are still in U3
9. USB4 CV performs U3 exit for all the UUT downstream ports
10. USB4 CV verifies that the UUT sends at least 3 LFPS Packets on each connected downstream port with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
11. USB4 CV verifies link initialization of the UUT downstream port according to Part 2 and Part 3 in TD 9.2

Part 3 – Exit U3 from the UUT

12. Initiate U3 entry according to Part 1
13. Perform wake from the UUT by:
 - a. Disconnect on each downstream port
 - b. Connect on each downstream port
 - c. Wake from the USB4 Device connected on each downstream port
14. USB4 CV verifies that the UUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
15. USB4 CV writes to PORTSC in the xHCI interface back to U0
16. USB4 CV verifies that the KG USB4 Host responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
17. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2
18. USB4 CV verifies that all connected downstream ports return to U0

Part 4 – Exit U3 from the UUT with Retry

19. Initiate U3 entry according to Part 1
20. Perform wake from the UUT by:
 - a. Disconnect on each downstream port
 - b. Connect on each downstream port
 - c. Wake from the USB4 Device connected on each downstream port
21. USB4 CV verifies that the UUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
22. Analyzer waits 10ms and verifies that the UUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 0
 - d. All other fields set to 0
23. Analyzer waits 100ms and verifies that the UUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
24. USB4 CV writes to PORTSC in the xHCI interface back to U0
25. USB4 CV verifies that the KG USB4 Host responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
26. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

UUT is a USB4 Hub (DFP)

Note: PUT is the downstream facing port of the UUT

Part 1 – Entry to U3

1. Perform link initialization in the upstream port of the UUT and in PUT according to TD 9.2
2. USB4 CV enables U3 in the PUT
3. USB4 CV verifies that the PUT requests entry to U3
4. USB4 CV verifies that the PUT accepts entry to U3
5. USB4 CV verifies there are no USB3 Tunneled Packets for 1 sec after entering to U3 state
6. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
7. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the PUT and in the Compliance Device is set and the *PLS* field value is 3h

Part 2 – Exit U3 from the UUT

8. USB4 CV requests wake from U3 by issue set feature request to the PUT
9. USB4 CV verifies that the PUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
10. Compliance Device responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
11. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

Part 3 – Exit U3 from the Compliance Device with Retry

12. Perform entry to U3 according to Part 1
13. Perform wake from U3 from the Compliance Device by issue wake
14. Compliance Device sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
15. USB4 CV verifies that the PUT responds with at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. U3 exit bit field set to 1
 - d. All other fields set to 0
16. USB4 CV verifies link initialization according to Part 2 and Part 3 in TD 9.2

A. Purpose

- Verify that the UUT can send and receive warm reset

B. Asserts:

- 9.1.1.1.7#2, 9.1.1.1.7#3, 9.1.1.1.7#6, 9.1.1.1.7#7

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_UFP1—USB3_01 (Hub UFP)
- AN_HUB_DFP1—USB3_03 (Hub DFP)
- AN_DEV_UFP1—USB3_01 (Peripheral Device)

D. Repetitions:

- Repeat the test while the PUT is in:
 - U0
 - U2
 - U3

E. Procedure:

Note: The test is run with a USB4 KG Device that supports:

- *USB3 Tunneling at USB 3.2 Gen2x1 speed*
- *USB3 Tunneling at USB 3.2 Gen2x2 speed*

UUT is a USB4 Host or USB4 Device

1. Perform link initialization according to TD 9.2
2. USB4 CV requests warm reset using PORTSC in the USB4 Host
3. USB4 CV verifies that the PUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. Warm_reset exit bit field set to 1
 - d. All other fields set to 0
4. For 100ms after the last LFPS Packet, USB4 CV verifies that there are no other USB3 Tunneled Packets
5. After warm reset timeout, USB4 CV verifies that the USB4 Host sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. All other fields set to 0
6. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
7. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the UUT is set to 0
8. USB4 CV verifies that the link returns to U0

UUT is a USB4 Hub

1. Perform link initialization according to TD 9.2
2. USB4 CV requests warm reset using SetPortFeature(PORT_BH_RESET)

3. USB4 CV verifies that the PUT sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. Warm_reset exit bit field set to 1
 - d. All other fields set to 0
4. For 100ms after the last LFPS Packet, USB4 CV verifies that there are no other USB3 Tunneled Packets
5. After warm reset timeout, USB4 CV verifies that the USB4 Host sends at least 3 LFPS Packets with:
 - a. PDF set to 0
 - b. term_en field set to 1
 - c. All other fields set to 0
6. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
7. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the UUT is set to 0
8. USB4 CV verifies that the link returns to U0

TD 9.6 Hot Reset Test (Host and Hub Only)

Note: This test is only performed on the DFP

A. Purpose

- Verify that the UUT can send and receive hot reset

B. Asserts:

- 9.1.1.2#1, 9.1.1.2#2, 9.1.1.2#3, 9.1.1.2#4

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_DFP1—USB3_03 (Hub DFP)

D. Procedure:

1. Perform link initialization according to TD 9.2
2. USB4 CV requests hot reset using PORTSC in the USB3 downstream port
3. USB4 CV verifies that the USB3 Downstream Adapter sends at least 3 OS Tunneled Packets with:
 - a. PDF set to 1
 - b. TS1 field set to 1
 - c. All other fields set to 0
4. USB4 CV verifies that the USB4 Device responds with at least 3 OS Tunneled Packets with:
 - a. PDF set to 1
 - b. TS1 field set to 1
 - c. All other fields set to 0
5. USB4 CV verifies that the USB3 Downstream Adapter sends at least 3 OS Tunneled Packets with:
 - a. PDF set to 1
 - b. TS2 field set to 1
 - c. Link Functionality bit 0 set to 1
 - d. All other fields set to 0
6. The Compliance Device responds with at least 3 OS Tunneled Packets with:
 - a. PDF set to 1
 - b. TS2 field set to 1
 - c. Link Functionality bit 0 set to 1
 - d. All other fields set to 0
7. USB4 CV verifies that the USB3 Downstream Adapter sends at least 3 OS Tunneled Packets with:
 - a. PDF set to 1
 - b. TS2 field set to 1
 - c. All other fields set to 0
8. The Compliance Device responds with at least 3 OS Tunneled Packets with:
 - a. PDF set to 1
 - b. TS2 field set to 1
 - c. All other fields set to 0
9. USB4 CV verifies that the link returns to U0
10. USB4 CV verifies that the *Actual Link Rate* field in ADP_USB_CS_4 is equal to the minimum between *Maximum Supported Link Rate* field in both the USB3 Downstream Adapter and the USB3 Upstream Adapter
11. USB4 CV verifies that the *USB Link Valid* field in ADP_USB_CS_4 in the UUT set to 0

TD 9.7 None Drop Packets Test

A. Purpose

- Verify that the UUT doesn't drop any USB3 Tunneled Packets when bandwidth is limited

B. Asserts:

- 9.1.1#8

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_UFP1—USB3_01 (Hub UFP)
- AN_HUB_DFP1—USB3_03 (Hub DFP)
- AN_DEV_UFP1—USB3_01 (Peripheral Device)

D. Procedure:

1. USB4 CV sets up a USB3 Path with 1 credit in the USB3 Adapters
2. Perform link initialization according to TD 9.2
3. USB4 CV transmits data from the USB4 Host to the USB4 Device for at least 1 minute
4. USB4 CV receives data between the USB4 Device and the USB4 Host for at least 1 minute
5. During the data transfer, the USB4 CV verifies that there are no recoveries over the USB3 tunnel

TD 9.8 Data Packet Traffic Test

Note: This test requires a USB 3.2 Device that generates data packets in different sizes. This can be done using one of the options below:

- Use the loopback device that is used for USB 3.2 certification (MUTT device)
- Use a USB4 exerciser that can generate USB3 Tunneled Packets in various sizes

A. Purpose

- Verify that the UUT can handle all data packet sizes

B. Asserts:

- 9.1.1#2, 9.1.1#9, 9.1.1.8#1, 9.1.1.8#2, 9.1.1.8#3, 9.1.1.8#4, 9.1.1.8#5, 9.1.1.8#6

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_UFP1—USB3_01 (Hub UFP)
- AN_HUB_DFP1—USB3_03 (Hub DFP)
- AN_DEV_UFP1—USB3_01 (Peripheral Device)

D. Procedure:

1. Perform link initialization according to TD 9.2
2. USB4 CV transmits data to and from the Compliance Device
 - a. Data is transmitted in data packets that carry between 1B and 2048B of data, where the first data packet contains 1B of data, the second data packet contains 4B of data, and each subsequent data packet contains an additional 4B of data (8B, 12B, etc.)
 - b. The data packet can be generated using any USB device
3. USB4 CV verifies that there are no recoveries over the USB3 tunnel for at least 1 min for each data packet size
4. USB4 CV verifies the following:
 - a. All data packets between 1B to 216B are transmitted as a single data packet that includes the DPH and DPP in the same packet. The type of the USB3 Tunneled Packet is Start DP Segment using PDF 4
 - b. All data packets between 217B to 468B are transmitted as two USB3 Tunneled Packets:
 - i. The first Tunneled Packet includes the DPH and part of DPP in the same packet. The type of the Tunneled Packet is Start DP Segment using PDF 4. The size of the Tunneled Packet is 256B
 - ii. The second Tunneled Packet includes the remaining data. The type of the Tunneled Packet is End DP Segment using PDF 6
 - c. All data packets between 469B to 2048B are transmitted as at least 3 USB3 Tunneled Packets:
 - i. The first Tunneled Packet includes the DPH and part of the DPP. The type of the Tunneled Packet is Start DP Segment using PDF 4. The size of the Tunneled Packet is 256B
 - ii. Any middle-Tunneled Packets include the continued data from the data packet. The type of the Tunneled Packet is Start DP Segment using PDF 5. The size of the Tunneled Packet is 256B
 - iii. The last USB3 Tunneled Packet includes any remaining data. The type of the Tunneled Packet is End DP Segment using PDF 6

A. Purpose

- Verify that the UUT can re-assembling USB3 Tunneled Packets into USB 3.2 Data Packets

B. Asserts:

- 9.1.1.8#11, 9.1.1.8#12, 9.1.1.8#13
- 9.1.3#1

C. Setup:

- EX_HOST_DFP1—USB3_02 (Host)
- EX_HUB_UFP1—USB3_02**Error! Reference source not found.** (Hub UFP)
- EX_HUB_DFP1—USB3_04 (Hub DFP)
- EX_DEV_UFP1—USB3_02(Peripheral Device)

D. Procedure:

1. Perform link initialization according to TD 9.2 between the UUT and the Exerciser

Part 1 – Missing Start DP Segment

2. Exerciser transmits a series of USB3 Tunneled Packets with 1024B of data that includes Start DP Segment, Middle DP Segment and End DP segment
3. Exerciser verifies that there is a link command from the UUT that responds successfully to the packet with LGOOD and LCRDT
4. Exerciser transmits a series of USB3 Tunneled Packets with 1024B of data that include only:
 - a. End DP Segment with PDF 6
 - b. Middle DP Segment with PDF 5
 - c. End DP Segment with PDF 6
5. For 1 sec, Exerciser verifies that there is no link command from the UUT that responds to the packet
6. Exerciser transmits a series of USB3 Tunneled Packets with 1024B of data that include:
 - a. Start DP Segment
 - b. Middle DP Segment
 - c. End DP segment
7. Exerciser verifies that the UUT sends a link command that responds to the packet with LBAD

Part 2 – Missing Middle DP Segment

8. Exerciser transmits a series of USB3 Tunneled Packets with 1024B of data that include only:
 - a. Start DP Segment with PDF 4 and End DP Segment with PDF 6
 - b. Start DP Segment with PDF 4, 1 Middle DP Segment with PDF 5 and End DP Segment with PDF 6
9. Exerciser verifies that the UUT sends a link command with PDF 2 that indicates on LBAD

Part 3 – Missing End DP Segment

10. Exerciser transmits a series of USB3 Tunneled Packets with 1024B of data that includes only:
 - a. Start DP Segment with PDF 4
 - b. 3 Middle DP Segment with PDF 5
 - c. Another Start DP Segment with PDF 4
11. Exerciser verifies that the UUT sends a link command with PDF 2 that indicates on LBAD

Part 4 – Missing single End DP Segment

12. Exerciser transmits a series of USB3 Tunneled Packets with 1024B of data that includes only:
 - a. Start DP Segment with PDF 4
 - b. 3 Middle DP Segment with PDF 5
13. Exerciser verifies that the UUT sends a link command with PDF 2 that indicates on LBAD in less than $t_{\text{Reassemble time}} + \text{PENDING_HP_TIMER}$

- A. Purpose:
 - Verify that a USB4 Host/Hub handles the ITP correctly
- B. Asserts:
 - 9.1.1.7#2, 9.1.1.7#3, 9.1.1.7#4, 9.1.1.7#7
- C. Setup:
 - AN_HOST_DFP1—USB3_01 (Host)
 - AN_HUB_UFP1—USB3_01 (Hub UFP)
 - AN_HUB_DFP1—USB3_03 (Hub DFP)
 - AN_DEV_UFP1—USB3_01 (Peripheral Device)
- D. Procedure:

Part 1 – Encapsulation Format

1. Perform link initialization according to TD 9.2 between the UUT and the Analyzer
2. While the link is in U0, the Analyzer captures packets for 1 sec
3. Find the first ITP packet in the trace and verify that:
 - a. PDF is 3
 - b. Length of the ITP packet is 0x1C
 - c. TMU Time Capture value is greater than zero
4. For each additional ITP packet in the trace, verify:
 - a. PDF is 3
 - b. Length of the ITP packet is 0x1C
 - c. TMU Time Capture value is greater than zero
 - d. Verify the following:

$$(\text{Current TMU time} - \text{Current Delta time}) - (\text{Previous TMU time} - \text{Previous Delta time}) == 125\mu \pm 1\mu\text{s}$$

Part 2 – Delta Check for Hub DFP (Hubs Only)

5. Perform link initialization according to TD 9.2 between the UUT UFP and the Analyzer
6. Perform link initialization according to TD 9.2 between the UUT DFP and the Analyzer
7. While the link is in U0, the Analyzer captures packets for 1 sec
8. USB4 Analyzer sends ITP packet with current TMU time + 125μs
9. Find the ITP packet in the downstream trace and verify that:
 - a. PDF is 3
 - b. Length of the ITP packet is 0x1C
 - c. TMU Time Capture value is greater than zero
 - d. Delay bit is set to 1

TD 9.11 Upstream BW Management Test (Host Only)

A. Purpose:

- Verify that the UUT implements Bandwidth Negotiation correctly

B. Asserts:

- 9.3.2#1, 9.3.2#5

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)

D. Procedure:

1. Perform Link Initialization according to TD 9.2
2. USB4 CV verifies that *Host Controller Ack* field is set to 0
3. USB4 CV verifies that *Consumed Upstream Bandwidth* field \leq *Allocated Upstream Bandwidth* field
4. USB4 CV sets the *Connection Manager Request* field to 1
5. USB4 CV waits until the *Host Controller Ack* field is set to 1
6. USB4 CV sets the *Allocated Upstream Bandwidth* field to be equal to the *Consumed Upstream Bandwidth* field
7. USB4 CV clears the *Connection Manager Request* field
8. USB4 CV waits until the *Host Controller Ack* field is clear
9. USB4 CV verifies that *Consumed Upstream Bandwidth* field \leq *Allocated Upstream Bandwidth* field
10. USB4 CV connects a USB 3.2 isochronous device to the topology
11. USB4 CV verifies that *Consumed Upstream Bandwidth* field \leq *Allocated Upstream Bandwidth* field
12. USB4 CV verifies that the Compliance Device did not enumerate

TD 9.12 Downstream BW Management Test (Host Only)

A. Purpose:

- Verify that the UUT implements Bandwidth Negotiation correctly

B. Asserts:

- 9.3.2#2, 9.3.2#5

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)

D. Procedure:

1. Perform Link Initialization according to TD 9.2
2. USB4 CV verifies that *Host Controller Ack* field is set to 0
3. USB4 CV verifies that *Consumed Downstream Bandwidth* field \leq *Allocated Downstream Bandwidth* field
4. USB4 CV sets the *Connection Manager Request* field to 1
5. USB4 CV waits until the *Host Controller Ack* field is set to 1
6. USB4 CV sets the *Allocated Downstream Bandwidth* field to be equal to the *Consumed Downstream Bandwidth* field
7. USB4 CV clears the *Connection Manager Request* field
8. USB4 CV waits until the *Host Controller Ack* field is clear
9. USB4 CV verifies that *Consumed Downstream Bandwidth* field \leq *Allocated Downstream Bandwidth* field
10. USB4 CV connects a USB 3.2 isochronous device to the topology
11. USB4 CV verifies that the *Consumed Downstream Bandwidth* field \leq *Allocated Downstream Bandwidth* field
12. USB4 CV verifies that the Compliance Device did not enumerate

TD 9.13 Path Teardown Test (Hosts and Hubs Only)

Note: For USB4 Hub, this test requires a USB 3.2 device connected to the DFP

A. Purpose:

- Verify that the UUT clears the *Path Enable* bit after a downstream disconnect

B. Asserts:

- 9.3.2#1, 9.3.2#2

C. Setup:

- AN_HOST_DFP1—USB3_01 (Host)
- AN_HUB_DFP1—USB3_03 (Hub DFP)

D. Procedure:

Part 1 – Path Teardown at Disconnect

1. Perform Link Initialization according to TD 9.2
2. Disconnect the USB4 Device from the downstream port of the UUT
3. USB4 CV waits 500ms from the disconnect
4. USB4 CV reads ADP_USB3_CS_0 and verifies that the *Path Enable* bit is 0
5. USB4 CV reads ADP_USB3_CS_4 and verifies that the *PLS* field is 5h
6. Perform Link Initialization according to TD 9.2

Part 2 – Path Teardown

7. Perform Link Initialization according to TD 9.2
8. USB4 CV performs path teardown according to the CM guide
9. USB4 CV waits 500ms from the disconnect
10. USB4 CV reads ADP_USB3_CS_0 and verifies that the *Path Enable* bit is 0
11. USB4 CV reads ADP_USB3_CS_4 and verifies that the *PLS* field is 5h
12. Perform Link Initialization according to TD 9.2
13. Verify that all USB4 and USB 3.2 Devices enumerate at the correct speed

TD 9.14 tPortConfiguration Test

A. Purpose:

- Verify that the tPortConfiguration timer is implemented correctly

B. Asserts:

- 9.2.1.2#1

C. Setup:

- EX_HOST_DFP1—USB3_02 (Host)
- **Error! Reference source not found.** EX_HUB_UFP1—USB3_02(Hub UFP)
- EX_HUB_DFP1—USB3_04 (Hub DFP)
- EX_DEV_UFP1—USB3_02 (Peripheral Device)

D. Procedure:

Part 1 – Delayed LMP Packet

1. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
2. Exerciser verifies that the UUT sent a Port Configuration LMP Packet in less than tPortConfiguration time
3. Exerciser sends a Port Configuration LMP Packet (tPortConfiguration – 1 μ s) time after entering U0
4. If the PUT is a DFP, the Exerciser sends a Port Configuration LMP Response after (tPortConfiguration – 1 μ s). Else skip to next step
5. Exerciser verifies that the link stays in U0 at lease for 1 sec

Part B – No LMP Packet

6. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
7. Exerciser verifies that the UUT sends Port Configuration LMP Packet within tPortConfiguration time
8. Exerciser doesn't send a Port Configuration LMP Packet
9. Exerciser verifies that the link goes to recovery within tPortConfiguration + 1 μ s

Part C – LMP Packet (DFP Only)

10. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
11. Exerciser verifies that the UUT sent a Port Configuration LMP Packet within tPortConfiguration time
12. Exerciser sends a Port Configuration LMP Packet within tPortConfiguration
13. Exerciser verifies that the link goes to recovery within tPortConfiguration + 1 μ s

TD 9.15 PENDING_HP_TIMER Test

A. Purpose:

- Verify that PENDING_HP_TIMER is implemented correctly

B. Asserts:

- 9.2.1.2#1

C. Setup:

- EX_HOST_DFP1—USB3_02 (Host)
- EX_HUB_UFP1—USB3_02 **Error! Reference source not found.** (Hub UFP)
- EX_HUB_DFP1—USB3_04 (Hub DFP)
- EX_DEV_UFP1—USB3_02 (Peripheral Device)

D. Procedure:

Part 1 – Delayed Response

1. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
2. Exerciser verifies that the UUT sent a Port Configuration LMP packet within tPortConfiguration time
3. Exerciser responds with LGOOD_N for Port Configuration LMP 500ns prior to the PENDING_HP_TIMER deadline
4. Exerciser continues the LMP handshake
5. Verify that the link stays in U0 for at least 1 sec

Part 2 – No Response

6. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
7. Exerciser verifies that the UUT sent a Port Configuration LMP packet within tPortConfiguration time
8. Exerciser doesn't respond with LGOOD_N for Port Configuration LMP
9. Exerciser sends a Port Configuration LMP packet within tPortConfiguration time
10. If the PUT is a DFP, the Exerciser sends a Port Configuration LMP Response. Else skip to next step
11. Verify that the link goes to recovery after the PENDING_HP_TIMER deadline and before the next PENDING_HP_TIMER expires

TD 9.16 PM_LC_TIMER Test (Hosts and Hubs Only)

A. Purpose:

- Verify that PM_LC_TIMER is implemented correctly

B. Asserts:

- 9.2.1.2#1

C. Setup:

- EX_HOST_DFP1—USB3_02 (Host)
- EX_HUB_DFP1—USB3_04 (Hub)

D. Procedure:

Part 1 – Delayed Response

1. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
2. USB4 CV enables U2 on the PUT
3. Exerciser verifies that the PUT sends a LGO_U2 Packet
4. Exerciser responds with a LAU before the PM_LC_TIMER deadline
5. Verify that the PUT transmits an LPMA after receiving the LAU
6. Verify that the link transitions to U2 for at least 1 sec

Part 2 – No Response

7. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
8. USB4 CV enables U2 on the PUT
9. Exerciser verifies that the PUT sends LGO_U2 Packet
10. Exerciser doesn't respond with LAU
11. Verify that the link transition to recovery after PM_LC_TIMER deadline and back to U0

TD 9.17 PM_ENTRY_TIMER Test (Hubs and Devices Only)

A. Purpose:

- Verify that PM_ENTRY_TIMER is implemented correctly

B. Asserts:

- 9.2.1.2#1

C. Setup:

- EX_HUB_UFP1—USB3_02**Error! Reference source not found.** (Hub)
- EX_DEV_UFP1—USB3_02 (Peripheral Device)

D. Procedure:

1. Perform Link Initialization according to TD 9.2 between the UUT and the Exerciser
2. USB4 CV enables U2 on the PUT
3. Exerciser sends a LGO_U2 Packet
4. Exerciser verifies that the PUT responds with a LAU to go to U2
5. Exerciser doesn't respond with LPMA
6. Verify that the PUT transitions to U2 after PM_ENTRY_TIMER expires
7. Verify that the link transitions to U2 for at least 1 sec

USB3 Mode Testing (Hubs and Devices Only)

TD 9.18 USB3 DFP Test

A. Purpose:

- Verify that the UUT incorporates an internal USB SuperSpeed Plus hub per the USB 3.2 Specification with the modifications defined in the USB4 Specification

B. Asserts:

- 9#5

C. Procedure:

1. The downstream ports that support USB 3.2 runs USB 3.2 link layer certification as defined in the USB 3.2 CTS while the UFP is in USB4 mode
2. Verify that all tests pass

TBT3 Mode Testing (Hubs and Devices Only)

TD 9.19 TBT3 Compatibility Mode Test

A. Purpose:

- Verify that the internal Host Controller in a TBT3-Compatible UUT is compliant to the USB 3.2 specification and xHCI specification

B. Asserts:

- TBD

C. Procedure:

1. USB4 CV checks that the UUT supports TBT3 compatibility mode by reading the *TBT3 Not Supported* field from Router_CS_6
 - a. If TBT3 is supported, continue to next step
 - b. If TBT3-Compatibility is not supported, end test here
2. Connect the UUT to a KG TBT3 Host
3. Establish TBT3 link with PCIe tunnel
4. Run xHCI certification on the internal Host Controller of the UUT